





110 103 00 906 D | silver

control.x | 3000 mm
track



- track control.x 3000 mm
- for surface mounting or suspended mounting
- VDE-compliant 3 (5)-circuit tracks
- control cables (DALI or 1-10V) integrated in a touch-proof manner
- compatible with new DALI adapters and all conventional Hoffmeister 3-circuit adapters
- mixed operation of different adapters is no problem
- Can also be used to operate emergency lighting luminaires
- control.x and 3-circuit accessories can be used
- tracks made of a stable, extruded aluminium profile
- 3 x 16A for particularly long track systems
- approved to be used within easy reach
- the track can be cut without reworking the copper conductors
- material: aluminium
- length: 3000 mm, width: 35,3 mm, height: 36,5 mm
- weight: 3,4 kg
- protection rating: IP20
- protection class I
- colour: silver
- 110 103 00 906 D

- Overview of accessories on the following page / s

110 103 00 906 D
accessory

Optional accessories

description accessory general	dimensions in mm	item number	pic.-No.
steelwire suspension, 2500 mm for control.x tracks or other profile systems		095 089 00 000	01
steelwire suspension, 5000 mm for control.x tracks or other profile systems		095 680 00 000	01
steelwire suspension, 10.000 mm for control.x tracks or other profile systems		095 681 00 000	01
end cap	LxWxH: 3 x 35,3 x 36,5	110 000 00 906	02
end supply connector, 3-circuit earth conductor position: right	LxWxH: 96 x 35,3 x 36,5	110 001 00 906	03
end supply connector, control.x earth conductor position: right	LxWxH: 96 x 35,3 x 36,5	110 001 00 906 D	03
end supply connector, 3-circuit earth conductor position: left	LxWxH: 96 x 35,3 x 36,5	110 002 00 906	04
end supply connector, control.x earth conductor position: left	LxWxH: 96 x 35,3 x 36,5	110 002 00 906 D	04
90° coupler, 3-circuit earth conductor position: outside	LxWxH: 61,7 x 61,7 x 36,5	110 003 00 906	05
90° coupler, control.x earth conductor position: outside	LxWxH: 61,7 x 61,7 x 36,5	110 003 00 906 D	05
90° coupler, 3-circuit earth conductor position: inside	LxWxH: 61,7 x 61,7 x 36,5	110 004 00 906	06
90° coupler, control.x earth conductor position: inside	LxWxH: 61,7 x 61,7 x 36,5	110 004 00 906 D	06
90° coupler, 3-circuit earth conductor position: outside with optional power input	LxWxH: 98,4 x 98,4 x 36,5	110 005 00 906	07
90° coupler, control.x earth conductor position: outside with optional power input	LxWxH: 98,4 x 98,4 x 36,5	110 005 00 906 D	07
90° coupler, 3-circuit earth conductor position: inside with optional power input	LxWxH: 98,4 x 98,4 x 36,5	110 006 00 906	08
90° coupler, control.x earth conductor position: inside with optional power input	LxWxH: 98,4 x 98,4 x 36,5	110 006 00 906 D	08
T coupler, 3-circuit earth conductor position: right with optional power input	LxWxH: 161,5 x 98,4 x 36,5	110 007 00 906	09
T coupler, control.x earth conductor position: right with optional power input	LxWxH: 161,5 x 98,4 x 36,5	110 007 00 906 D	09
T coupler, 3-circuit earth conductor position: left with optional power input	LxWxH: 161,5 x 98,4 x 36,5	110 008 00 906	10
T coupler, control.x earth conductor position: left with optional power input	LxWxH: 161,5 x 98,4 x 36,5	110 008 00 906 D	10
X coupler, 3-circuit with optional power input	LxWxH: 161,5 x 161,5 x 36,5	110 009 00 906	11

110 103 00 906 D
accessory

Optional accessories

description accessory general	dimensions in mm	item number	pic.-No.
X coupler, control.x with optional power input	LxWxH: 161,5 x 161,5 x 36,5	110 009 00 906 D	11
coupler, 3-circuit	LxWxH: 2 x 35,3 x 36,5	110 010 00 906	12
coupler, control.x	LxWxH: 2 x 35,3 x 36,5	110 010 00 906 D	12
intermediate supply connector, 3-circuit	LxWxH: 161,5 x 35,3 x 36,5	110 011 00 906	13
intermediate supply connector, control.x	LxWxH: 161,5 x 35,3 x 36,5	110 011 00 906 D	13
Adjustable-coupler, 3-circuit	LxWxH: 124,5 x 124,5 x 124,5	110 012 00 906	14
Adjustable-coupler, control.x	LxWxH: 124,5 x 124,5 x 124,5	110 012 00 906 D	14
reinforcement, for intermediate supply connector	LxW: 192 x 32	110 015 00 906	15
reinforcement, for 90° connectors without an optional feed-in	LxW: 75 x 75	110 016 00 906	16
reinforcement, for 90° connectors with an optional feed-in	LxW: 111,8 x 111,8	110 017 00 906	17
reinforcement, for T-connectors with an optional feed-in	LxW: 191,5 x 111,8	110 018 00 906	18
reinforcement, for X connectors with an optional feed-in	LxW: 191,5 x 191,5	110 019 00 906	19
cover, for end-supply connector to cover connectors and supply connectors in the case of flanged tracks	LxW: 104 x 53	110 020 00 906	20
cover, for intermediate supply connector to cover connectors and supply connectors in the case of flanged tracks	LxW: 161 x 53	110 021 00 906	21
cover, for 90° connectors without an optional feed-in to cover connectors and supply connectors in the case of flanged tracks	LxW: 70,3 x 70,3	110 022 00 906	22
cover, for 90° connectors with an optional feed-in to cover connectors and supply connectors in the case of flanged tracks	LxW: 107 x 107	110 023 00 906	23
cover, for T-connectors with an optional feed-in to cover connectors and supply connectors in the case of flanged tracks	LxW: 161 x 107	110 024 00 906	24
cover, for X connectors with an optional feed-in to cover connectors and supply connectors in the case of flanged tracks	LxW: 161 x 161	110 025 00 906	25
intermediate cover, for coupler to cover couplers in the case of flanged tracks	W: 2	110 026 00 906	26
safety outlet-socket, single with 3-circuit universal adapter for control.x tracks	LxWxH: 60 x 60 x 90	093 619 00 721	27
pendent tube for suspension of tracks	Ø: 13	093 700 00 721	28
clamp, 2 pieces for ceiling mounted installation for control.x tracks		093 710 00 906	29
suspension hook for control.x tracks	H: 67	093 720 00 721	30
clamp, 2 pieces to be mounted on suspended ceilings for control.x tracks		093 725 00 906	31
reinforcement clamp for reinforcing the joints in the case of suspended tracks for control.x tracks	LxWxH: 132 x 33 x 12	093 734 00 906	32
wall bracket for wall mounted installation of control.x tracks	LxWxH: 135 x 32 x 100	101420	33
safety outlet-socket, 1-fach with 3-circuit universal adapter for control.x tracks	LxWxH: 60 x 60 x 89	110 029 00 906	34

110 103 00 906 D
accessory

Optional accessories

description accessory general	dimensions in mm	item number	pic.-No.
control.x adapter, DALI for control.x tracks	LxWxH: 77 x 35,3 x 39	110 030 00 906 D	35
control.x adapter, DALI for control.x tracks	LxWxH: 77 x 35,3 x 39	110 031 00 906 D	36

